



**Fourth Semester B.E. Degree Examination, June/July 2016**  
**Signals and Systems**

Time: 3 hrs.

Max. Marks:100

**Note: Answer any FIVE full questions, selecting atleast TWO questions from each part.**

**PART – A**

- 1 a. Sketch the even and odd part of the signals shown in Fig. Q1(a). (06 Marks)





Fig.Q1(a)

- b. For the signal  $x(t)$  and  $y(t)$  shown in Fig.Q1(b) sketch the signals :

- i)  $x(t+1) - y(t)$   
 ii)  $x(t) \cdot y(t-1)$ .

(06 Marks)





Fig.Q1(b)

- c. Determine whether the system described by the following input/output relationship is  
 i) memory less ii) causal iii) time invariant iv) linear.

i)  $y(t) = x(2-t)$

ii)  $y[n] = \sum_{k=0}^{\infty} 2^k x[n-k]$ .

(08 Marks)

- 2 a. Compute the following convolutions :

i)  $y(t) = e^{-2t} u(t-2) * \{u(t-2) - u(t-12)\}$

ii)  $y[n] = \alpha^n \{u[n] - u[n-6]\} * 2\{u[n] - u[n-15]\}$ .

(14 Marks)

- b. Prove the following :

i)  $x(t) * \delta(t-t_0) = x(t-t_0)$

ii)  $x[n] * u[n] = \sum_{k=-\infty}^n x[k]$ .

(06 Marks)

- 3 a. Identify whether the systems described by the following impulse responses are memory-less, causal and stable.
- $h(t) = 3\delta(t-2) + 5\delta(t-5)$
  - $h[n] = 2^n u[-n]$
  - $h[n] = (\frac{1}{2})^n \delta[n]$ .
- (09 Marks)
- b. Find the natural response and the forced response of the system described by the following differential equation:  $\frac{d^2 y(t)}{dt^2} - 4y(t) = \frac{d}{dt}x(t)$ , if  $y(0) = 1$  and  $\frac{d}{dt}y(t)|_{t=0} = -1$ . (08 Marks)
- c. Write the difference equation for the system depicted in Fig. Q3(c). (03 Marks)




Fig. Q3(c)

- 4 a. State and prove the Parseval's relation for the Fourier series representation of discrete time periodic signals. (06 Marks)
- b. i) Find the DTFS of the signal  $x(t) = \sin[5\pi t] + \cos[7\pi t]$
- ii) Find the FS of the signal shown in Fig. Q4(b)(ii). (08 Marks)




Fig. Q4(b)(ii)

- c. If the FS representation of periodic signal  $x(t)$  is  $x(t) \xleftrightarrow{FS, \omega_0} \frac{2\sin[K \omega_0 T_0]}{T K \omega_0}$  where  $\omega_0 = \frac{2\pi}{T}$  then find the FS of  $y(t)$  without computing  $x(t)$ :
- $y(t) = x(t+2)$
  - $y(t) = \frac{d}{dt}x(t)$ .
- (06 Marks)

## PART - B

- 5 a. i) Compute the DTFT of  $x[n] = (\frac{1}{2})^n u[n+2] + (\frac{1}{2})^n u[n-2]$
- ii) Find FT of the signal shown in Fig. Q5(a)(ii). (10 Marks)




Fig. Q5(a)(ii)

- b. Find inverse FT of the following  $x(j\omega)$ :

i)  $x(j\omega) = \frac{j\omega}{(j\omega)^2 + 6j\omega + 8}$

ii)  $x(j\omega) = j \cdot \frac{d}{d\omega} \frac{e^{3j\omega}}{2 + j\omega}$ .

(10 Marks)

- 6 a. Determine output of the LTI system whose I/P and the impulse response is given as :
- $x(t) = e^{-2t}u(t)$  and  $h(t) = e^{-3t}u(t)$
  - $x[n] = (1/2)^n u[n]$  and  $h[n] = \delta[n - 4]$ . (08 Marks)
- b. Find the Fourier transform of the signal  $x(t) = \cos \omega_0 t$  where  $\omega_0 = \frac{2\pi}{T}$  and  $T$  the period of the signal. (04 Marks)
- c. State the sampling theorem and briefly explain how to practically reconstruct the signal. (08 Marks)
- 7 a. State and prove differentiation in  $z$ -domain property of  $z$ -transforms. (06 Marks)
- b. Use property of  $z$ -transforms to compute  $x(z)$  of :
- $x[n] = n \sin(\pi n/2) u[-n]$
  - $x[n] = (n-2)(1/2)^n u[n-2]$ . (06 Marks)
- c. Find the inverse  $z$ -transforms of
- $x(z) = \frac{z^2 - 2z}{(z^2 + \frac{3}{2}z - 1)} \quad \frac{1}{2} < |z| < 2$
  - $x(z) = \frac{z^3}{(z - \frac{1}{2})} \quad |z| > \frac{1}{2}$ . (08 Marks)
- 8 a. Determine the impulse response of the following transfer function if :
- The system is causal
  - The system is stable
  - The system is stable and causal at the same time :  $H(z) = \frac{3z^2 - z}{(z-2)(z + \frac{1}{2})}$ . (08 Marks)
- b. Use unilateral  $z$ -transform to determine the forced response and the natural response of the system described by:  $y[n] - \frac{1}{4}y[n-1] - \frac{1}{8}y[n-2] = x[n] + x[n-1]$  where  $y[-1] = 1$  and  $y[-2] = 1$  with I/P  $x[n] = 3^n u[n]$ . (12 Marks)

\*\*\*\*\*